

| LAMP TYPE | WATTS | ACTUAL LENGTH (w/ Sockets in Inches) | ILLUMINATED LENGTH (w/ Sockets in Inches) | SOCKET TYPE | NUMBER OF LAMPS REGULATED PER MODEL | | | | MODEL SERIES |
|---|-------|--|---|-------------|---|---|-------------------------------------|-------------------------|---------------------------|
| | | | | | 1 | 2 | 3 | 4 | |
| Standard Performance/OUTPUT - 400mA T5's: All are 5/8th (.63) inches in Diameter) | | | | | | | | | |
| F4/T5 | 4 | 6 | 1 | Mini | FN0416-2 | FN0416-2 | FN0424-4 | FN0424-4 | 400 |
| F6/T5 | 6 | 9 | 4 | Mini | FN0416-2 | FN0416-2 | FN0436-4 | FN0436-4 | 400 |
| F8/T5 | 8 | 12 | 7 | Mini | FN0416-2 | FN0436-4 | FN0436-4 | FN0448-4 | 400 |
| F10/T5 | 10 | 17 | 12 | Mini | FN0416-2 | FN0436-4 | FN0464-4DV | FN0464-4DV | 400 |
| F13/T8 | 13 | 21 | 16 | Mini | FN0424-4 | FN0448-4 | | | 400 |
| T8's:: All are 1.0 inch in Diameter... | | | | | | | | | |
| F15/T8 | 15 | 18 | 10 | Med. | FN0624-1 | FN0648-2 | FN0696-4 HNP0480-3 | FN0696-4 HN06120-4 | 400, 600 |
| F30/T8 | 30 | 36 | 28 | Med. | FN0648-2 | HN06120-4 | | | |
| FO40/T8 | 40 | 60 | 52 | Med. | FN0696-4 | | | | |
| T12's: All are 1.5 inches in Diameter... | | | | | | | | | |
| F14/T12 | 14 | 15 | 3 | Med. | FN0624-1 | FN0648-2 | | | 600 |
| F15/T12 | 15 | 18 | 6 | Med. | FN0624-1 | FN0648-2 | | FN0696-4 | |
| F20/T12 | 20 | 24 | 12 | Med. | FN0624-1 | FN0648-2 | | FN0696-4 | |
| F30/T12 | 30 | 36 | 24 | Med. | FN0648-2 | FN0696-4 | HN06120-4 | FN06144-4 | |
| F40/T12 | 40 | 48 | 36 | Med. | FN0648-2 | FN0696-4 | FN06144-4 | FN06192-4 | |
| High Performance/OUTPUT - 800mA | | | | | T8's: All are 1.0 inch in Diameter... | | | | |
| F15/T8/HO | 30 | 18 | 10 | Med. | HN1024-1 FN1124-1 | | FN1096-4 | | 1000, 1100 |
| T12's: All are 1.5 inches in Diameter... | | | | | | | | | |
| F24/T12/HO | 32 | 35 | 6 | RDC | HN1024-1 FN1124-1 | FN1048-2 | | FN1096-4 | 1000, 1100 |
| F36/T12/HO | 44 | 36 | 18 | RDC | FN1048-2 | FN1096-4 | FN10120-4 | FN10144-4 | 1000 |
| F48/T12/HO | 60 | 48 | 30 | RDC | FN1048-2 | FN1096-4 | FN10144-4 | FN10192-4 | 1000 |
| F72/T12/HO | 85 | 72 | 54 | RDC | FN1096-4 | FN10144-4 | | | 1000 |
| F96/T12/HO | 110 | 96 | 78 | RDC | FN1096-4 | FN10192-4 | | | 1000 |
| Very High Performance/OUTPUT - 1500mA | | | | | T12's: All are 1.5 inches in Diameter... | | | | |
| FA20/T12/VHO | 57 | 24 | 12 | Med. | FN2024-1 HN2024-1 | FN2048-2 HN2048-2 | | FCC1696-2 FN1896-4 | 1600, 1800, 2000 |
| FA28/T12/VHO | 68 | 28 | 13 | Med. | FN2048-2 | FN1872-2 | FCC1696-2 FN1896-4 | FN23120-4 HN23120-4 | 1600, 1800, 2000, 2300 |
| FA30/T12/VHO | 57 | 36 | 24 | Med. | FN2048-2 | FN1872-2 | FN18120-4 FN23120-4 HN23120-4 | FN16144-4 | 1600, 1800, 2000, 2300 |
| F48/T12/VHO | 115 | 48 | 30 | RDC | FN2048-2 HN2048-2 | FCC1696-2 FN1896-4 FN2396-4 HN2396-4 | FN16144-4 | FN16192-4 FCC16192-2 | 1600, 1800, 2000, 2300 |
| F60/T12/VHO | 135 | 60 | 42 | RDC | FN1872-2 | FN18120-4 FN23120-4 HN23120-4 | FN16192-4 FCC16192-2 | | 1600, 1800, 2300 |
| F72/T12/VHO | 165 | 72 | 54 | RDC | FN1872-2 | FN16144-4 | | | 1600, 1800 |
| F96/T12/VHO | 215 | 96 | 78 | RDC | FCC1696-2 FN1896-4 FN2396-2 HN2396-2 | FN16192-4 FCC16192-2 | | | 1600, 1800, 2300 |
| TYPE: TWIN TUBES All are RAPID START | | | | | | | | | |
| GE F18 BIAx | 18 | 9 | | 2G11 | FN0648-2 | FN0696-4 | | | 600 |
| OS 24W Dulux | 24 | 11 | | 2G11 | FN0648-2 | FN0696-4 | | | 600 |
| OS 40W Dulux | 40 | 21 | | 2G11 | FN0464-4DV | HN06120-4 | | | 400, 600 |
| OS 36W Dulux | 36 | 14.75 | | 2G11 | FN0464-4DV | HN06120-4 | | | 400, 600 |
| GE F40 BIAx | 40 | 21 | | 2G11 | FN0464-4DV | HN06120-4 | | | 400, 600 |
| OS 55W Dulux | 55 | 19.5 | | 2G11 | FN0696-4 | FN06144-4 | | | 600 |
| PL-L 80W | 80 | 21 | | 2G11 | FN0696-4 | FN06144-4 | | | 600 |
| TYPE: CIRCULAR | | | | | | | | | |
| FC6/T9 | 20 | n/a | 6 | 4-PIN | FN0624-1 | FN0648-2 | | FN0696-4 | 600 |
| FC8/T9 | 22 | n/a | 8 | 4-PIN | FN0516-1 | FN0664-2 | | | 500, 600 |
| FC12/T9 | 38 | n/a | 12 | 4-PIN | FN0648-2 | FN0696-4 | FN06144-4 | | 600 |
| S&Y RING | 8 | n/a | 3 | Mini | FN0516-1 | FN0424-4 | FN0436-4 | | 400, 500 |